



Features:

- Universal AC input / Full range
- No load power consumption<0.3W
- Pass energy star (CEC) level IV for full series
 Meet energy star (CEC) level V for 12~48V
- Meet EISA 2007(Energy Independence and Security Act)
- 3 pole AC inlet IEC320-C14
- Class I power (with earth pin)
- Protections: Short circuit / Overload / Over voltage / Over temperature
- Fully enclosed plastic case
- LED indicator for power on
- Approvals: UL / CUL / TUV / BSMI / CCC / CB / FCC / CE
- Pass LPS for full series
- · 2 years warranty




ORDER NO.		GS60A05-P1J	GS60A07-P1J	GS60A09-P1J	GS60A12-P1J	GS60A15-P1J	GS60A18-P1J	GS60A24-P1J	GS60A48-P1
ОИТРИТ	SAFETY MODEL NO.	GS60A05	GS60A07	GS60A09	GS60A12	GS60A15	GS60A18	GS60A24	GS60A48
	DC VOLTAGE Note.2	5V	7.5V	9V	12V	15V	18V	24V	48V
	RATED CURRENT	6A	6A	6A	5A	4A	3.33A	2.5A	1.25A
	CURRENT RANGE	0 ~ 6A	0 ~ 6A	0 ~ 6A	0 ~ 5A	0 ~ 4A	0 ~ 3.33A	0 ~ 2.5A	0 ~ 1.25A
	RATED POWER (max.)	30W	45W	54W	60W	60W	60W	60W	60W
	RIPPLE & NOISE (max.) Note.3	100mVp-p	100mVp-p	100mVp-p	100mVp-p	100mVp-p	150mVp-p	180mVp-p	240mVp-p
	VOLTAGE TOLERANCE Note.4	±5.0%	±5.0%	±5.0%	±3.0%	±3.0%	±3.0%	±3.0%	±2.5%
	LINE REGULATION Note.5	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%	±1.0%
	LOAD REGULATION	±5.0%	±5.0%	±5.0%	±3.0%	±3.0%	±3.0%	±3.0%	±2.5%
	SETUP, RISE TIME Note.7	600ms, 30ms / 2	230VAC 600	Oms, 30ms / 115	VAC at full load				
	HOLD UP TIME (Typ.)	50ms / 230VAC 15ms / 115VAC at full load							
INPUT	VOLTAGE RANGE	90 ~ 264VAC 135 ~ 370VDC							
	FREQUENCY RANGE	47 ~ 63Hz							
	EFFICIENCY (Typ.)	79.5%	84%	85%	88%	88.5%	88.5%	90%	92%
	AC CURRENT	1.4A/115VAC 1A/230VAC							
	INRUSH CURRENT (max.)	65A / 230VAC							
	LEAKAGE CURRENT(max.)	0.75mA / 240VAC							
PROTECTION		105 ~ 150% rated output power							
	OVERLOAD	Protection type: Hiccup mode, recovers automatically after fault condition is removed							
		5.25 ~ 6.75V		9.45 ~ 12.15V		15.75 ~ 20.25V		25.2 ~ 32.4V	50.4 ~ 64.8V
	OVER VOLTAGE	Protection type: Shut down o/p voltage, re-power on to recover							
		RTH2 > 70°C							
	OVER TEMPERATURE	Protection type: Shut down o/p voltage, re-power on to recover							
ENVIRONMENT	WORKING TEMP.	-10 ~ +50°C (Refer to output load derating curve)							
	WORKING HUMIDITY	20% ~ 90% RH non-condensing							
	STORAGE TEMP., HUMIDITY	-20 ~ +85°C, 10 ~ 95% RH							
	TEMP. COEFFICIENT	±0.03% / °C (0~50°C)							
	VIBRATION	10 ~ 500Hz, 2G 10min./1cycle, period for 60min. each along X, Y, Z axes							
SAFETY & EMC (Note. 6)	SAFETY STANDARDS	UL60950-1, TUV EN60950-1, BSMI CNS14336, CCC GB4943 approved							
	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:1.5KVAC O/P-FG:0.5KVAC							
	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C / 70% RH							
	EMI CONDUCTION & RADIATION	Compliance to EN55022 class B, FCC PART 15 / CISPR22 class B, CNS13438 class B, GB9254 class B							
	HARMONIC CURRENT	Compliance to EN61000-3-2.3, GB17625.1							
	EMS IMMUNITY	Compliance to EN61000-4-2,3,4,5,6,8,11, light industry level, criteria A							
OTHERS	MTBF	711Khrs min. MIL-HDBK-217F(25°C)							
	DIMENSION	125*50*31.5mn		,					
	PACKING		0.31Kg; 40pcs/13.4Kg/0.91CUFT						
CONNECTOR	PLUG	Standard type P1J: $2.1\phi * 5.5\phi * 11$ mm, tuning fork type, center positive for stock; Other type available by customer requested							
	CABLE	See page 2 : Other type available by customer requested							

- 2. DC voltage: The output voltage set at point measure by plug terminal & 50% load.
- 3. Ripple & noise are measured at 20MHz by using a 12" twisted pair terminated with a 0.1uf & 47uf capacitor.
- 4. Tolerance: includes set up tolerance, line regulation, load regulation.
- 5. Line regulation is measured from low line to high line at rated load.
- 6. The power supply is considered a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets EMC directives.
- 7. Length of set up time is measured at first cold start. Turning ON/OFF the power supply may lead to increase of the set up time.



■ Mechanical Specification

Case No. 974A Unit:mm



■ Plug Assignment

Standard plug: P1J (option)

P1J					
P/N	ОИТРИТ				
CENTER	+				

